

HANDHELD COMPUTER

DB6

USER'S GUIDE

Notice

The company reserves the right to revise this publication or to change its contents without any notice. Information contained herein is for reference only, and does not constitute a commitment on the part of the manufacturer or any subsequent vendor. They assume no responsibility or liability for any error or inaccuracy that may appear in this publication nor are they in anyway responsible for any loss or damage resulting from the use (or misuse) of this publication.

Any of the software described in this manual is sold or licensed "as is". Should the programs prove defective following purchase, the buyer (and not the manufacturer, its distributor, or its dealer) assumes the entire cost of all necessary servicing, repair and any incidental or consequential damages resulting from any software defects.

Copyright © 2010 CReTE Systems Inc.

Trademarks

All other brand and product names are trademarks or registered trademarks of their respective companies.

Regulatory Information/ Disclaimers

Installation and use of this computer must be in strict accordance with the instructions included in the user documentation provided with the product. Any changes or modifications (including the antennas) made to this device that are not expressly approved by the manufacturer may void the user's authority to operate the equipment.

The manufacturer is not responsible for any radio or television interference caused by unauthorized modification of this device, or the substitution of the connecting cables and equipment other than manufacturer specified. It is the responsibility of the user to correct any interference caused by such unauthorized modification, substitution or attachment. Manufacturer and its authorized resellers or distributors will assume no liability for any damage or violation of government regulations arising from failing to comply with these guidelines.

FCC (Federal Communications Commission) Statement

This equipment has been tested and found to comply with the limits for a Class B digital device pursuant part 15 of the FCC Rules. These limits are designed to provide reasonable protection against harmful interference in a residential installation.

This equipment generates, uses, and radiates radio frequency energy. If not being installed and used in accordance with the instructions, it may cause harmful interference to radio communications. However, there is no guarantee that interference will not occur in a particular installation. If this equipment does cause harmful interference to radio or television reception, which can be determined by turning the equipment off and on, the user is encouraged to try to correct the interference by one or more of the following measures:

- Re-orient or relocate the receiving antenna.
- Increase the separation between the equipment and receiver.
- Connect the equipment into an outlet on a circuit different from that to which the receiver is connected.
- Consult the dealer or an experienced radio/TV technician for help.

This device complies with Part 15 of the FCC Rules. Operation is subject to the following two conditions:

- This device may not cause harmful interference.
- This device must accept any interference received, including interference that may cause undesired operation.



FCC Caution

To assure continued compliance, any changes or modifications not expressly approved by the party responsible for compliance could void the user's authority to operate this equipment. (Example - use only shielded interface cables when connecting to computer or peripheral devices).

CE

Products with the CE Marking comply with both the EMC Directive (2004/108/EC) and the Low Voltage Directive (2006/95/EC) issued by the Commission of the European Community.

Compliance with these directives implies conformity to the following European Norms:

EN55022	CISPR 22 Radio Frequency Interference
EN55024	EN61000-4-2, EN61000-4-3, EN61000-4-4, EN61000-4-5, EN61000-4-6, EN61000-4-8, EN61000-4-11, EN61000-3-2, EN61000-3-3, Generic Immunity Standard
LVD	EN 60950 Product Safety, IEC 60950-1: 2005

R&TTE (CE) Manual Regulatory Requirement

WLAN - IEEE 802.11a/b/g/n

802.11a/b/g/n Restrictions:

European standards dictate maximum radiated transmit power of 100mW EIRP and frequency range 2.400-2.4835 GHz. In France, the equipment must be restricted to the 2.4465-2.4835 GHz frequency range and must be restricted to indoor use.

CE Declaration of Conformity



It is confirmed to comply with the requirements set out in the Council Directive on the approximation of the laws of the member states relating to Electromagnetic Compatibility Directive (2004/108/EC), Low-voltage Directive (2006/95/EC) and the procedures given in R&TTE Directive (99/5/EC).

The equipment was passed, and the equipment test was performed according to the following European standards:

EN 300 328 V1.7.1:2006

EN 301 893 V1.4.1(2007-07)

EN 301 V1.8.1 2008-04 / EN 301 489-17 V1.3.2 2008-04

EN 50371:2002

EN 60950-1: 2005

UL, TÜV: AC Adapter (TÜV includes EN60950 LVD)

Environmental Information, Material Safety & Recycling

All materials used in the manufacturing of this equipment are recyclable or environmentally friendly. Please recycle the packing materials by the local regulations at the end of the product's service life.

Notice:

- The equipment may still contain tiny amount of hazardous substances for health and environment, though those are below control level.
- To avoid spreading such substances into the eco system, and to minimize the pressure on the natural, you are encouraged to use the appropriate take-back for reusing or recycling most of the materials in a safe way after the service life.
- The crossed bin symbol indicates proper disposal is required.
- For more information on collection, reuse and recycling, please consult the local or regional waste administration for more information.
- You can also contact with the dealer for more information on the environmental details of the equipment.

Content

Chapter One- Getting Start	1
Unpacking	1
Workplace	2
Ruggedness	3
Appearance Overview.....	4
Front	4
Rear.....	5
Side A	6
Side B.....	7
Side C.....	8
Side D.....	8
Ready for Use	9
Mounting the Battery	9
Connecting with AC Adapter.....	10
Turning OFF the Power	12
Chapter Two- Operating Information	13
Boot up	13
Power on Self Test (POST)	13

Stop Using Your Handheld Computer	14
Shut down	14
Standby.....	15
Hibernate.....	15
Using Indicators and Keypad	16
Indicators.....	16
Keypad Hotkey	17
Using Application Menu	18
Using Touch Screen	19
Using Microphone	22
Using Fingerprint Sensor (Optional)	24
Operating Wireless Devices.....	26
Bluetooth	26
WWAN (Optional).....	30
Using Camera (Optional)	34
Taking Pictures	35
Recording Video.....	35
Chapter Three- Managing Power	37
Charging Battery	37
Checking the Battery Level.....	38

Power Conservation.....	38
Replacing Battery.....	39
Power Saving Tips	39
Supporting ACPI.....	40
AC Adapter and AC Power Cord Safety	41
Battery Precautions.....	42
Chapter Four- BIOS Setup.....	44
Main Menu	45
Advanced Menu	46
Security Menu	48
Exit Menu	49
Chapter Five- Drivers and Applications	50
Chipset	54
Graphic Controller.....	54
Touch Screen	55
Stickpointer.....	56
Audio	57
Fingerprint Sensor (Optional).....	58
Wireless Devices.....	59
Bluetooth	59

WLAN (Optional)	60
WWAN (Optional)	61
GPS (Optional)	62
Device Power Manager.....	63
Gigabit LAN (Optional).....	64
Chapter Six- Specification	65
Standard System Unit	65
CPU	65
Memory.....	65
Graphic Controller	65
HDD.....	66
Audio	66
Display.....	66
Communication	67
I/O Ports	67
Battery	67
AC Adapter	67
Dimensions & Weight.....	68
Case Material & Colors	68
Certification	68

Optional Devices and Accessories.....	69
Camera.....	69
Communication	69
I/O Ports	69
Security.....	70
Chapter Seven- Maintenance and Service	71
Cleaning.....	71
RMA Service	73

Chapter One- Getting Start

Unpacking

After unpacking, the followings are the standard items along with your computer. If there is any missing or damaged, please notify the dealer immediately.

- Handheld Computer Unit
- AC Adapter
- AC Power Cord
- Utility DVD
- Stylus Pen
- Quick Guide

Workplace

A clean and moisture-free environment is preferred. Make room for air circulation. Remember to avoid areas from:

- Sudden or extreme changes in temperature.
- Extreme heat.
- Strong electromagnetic fields (near television set, motor rotation area, etc.).
- Dust or high humidity.

If it is necessary to work in a hostile environment, please regularly maintain your computer by cleaning dust, water, and etc. to keep it in an optimal condition.

Environmental Ratings-

Operating Temperature:	0 ~ +40 °C (DB6-I)/ -20 ~ +50 °C (DB6-M)
Operating Altitude:	0 ~ 4,572 meters
Operating Humidity:	Up to 95%

Ruggedness

The computer is designed with rugged features such as vibration, shock, dust, and rain/ water protection. However, it is still necessary to provide appropriate protection while operating in harsh environments.

Since the handheld computer is passed MIL-STD-810G for the temperature, vibration, shock, humidity and salt fog tests, and IP55 (I Model) or IP65 (M model) for dust and water resistant tests, the handheld computer is therefore a fully-rugged one.

Appearance Overview

Before starting to use your handheld computer, we suggest you to have a quick glance at it to know the external components well.

Front

1. Embedded Antennas:

Embedded antennas for wireless application

2. LCD:

For displaying the output of the handheld computer

3. LED Indicators:


For indicating status by different colors and lighting methods.

4. Keypad:

For quick operation



Rear



1. Fingerprint Reader (Optional):
Scanning users' fingerprints for security

2. 2M AF Camera (Optional):
Capturing images and recording videos

3. Speaker:
Internal speaker

4. Battery Lock:
Locating the battery correctly and locking with it.

5. Stylus Pen:
Tool pen for using touch screen

6. Battery:
Swappable Li-Ion Battery

Side A



Location 1 & 2 Standard:


No Function

Location 1 & 2 Optional:

(Select 2 out of 7)

- a. Sealed USB
- b. Sealed Gigabit LAN (Trade-off: WLAN)
- c. Sealed Audio
- d. GPS SMA Antenna
- e. Wi-Fi SMA Antenna
- f. HSDPA/ UMTS SMA Antenna
- g. Bluetooth SMA Antenna

Side B



DC Power Jack:

For external power supply and power charging

Location 5 Standard:

No Function

Location 5 Optional:

Expansion POGO Connector

Signals consisted:

- a. USB x 1
- b. COM1 (RS232)
- c. RGB (Trade-off: Cradle RGB)
- d. Gigabit LAN
- e. DC In

Side C




Location 4

**Location 4-
Cradle POGO Connector:**
For connecting with the
optional cradle.

Side D

Standard I/O Ports:



Location 3- Standard I/O Ports:

- 1. SIM Card Slot**
For Inserting SIM card
- 2. USB 2.0 Port (Host)**
Connecting with USB
Devices
- 3. SD Card Slot**
For reading SD card

Ready for Use

After taking a quick look at your handheld computer, the following illustrations will get you ready for using it.

Mounting the Battery

1. Mount the battery into the battery bay.



2. Use a suitable-size coin to lock.



Connecting with AC Adapter

1. Insert the DC Jack to the end and lock the connector well clockwise.



2. Plug the AC cord to the AC adapter.



3. Plug the AC cord to a right electrical outlet.

Turning ON the Power

1. Make sure the battery is mounted or connect all power cords well for the stable power supply.
2. Now, you are able to turn ON the power of your handheld computer by pressing "Power Button".

Press  on the keypad to turn on the power of your handheld computer.

Note:

- The power is able to be ON without any battery mounted once all the power cords are connected well.
- Please see more information in "Operating Information".



Turning OFF the Power

Directly click “**Shut down**” from your OS to turn OFF the power of your handheld computer.

Note:

- The above-mentioned description is a standard way to turn OFF the power. Directly turn OFF the power by pressing “Power Button” will cause data lose and is not suggested.
- There are still other ways to stop your handheld computer from operating, see more information in “Operating Information”.

Chapter Two- Operating Information

Start Using Your Handheld Computer

Always turning on your handheld computer by using the power button, this is a standard operating procedure to start using your handheld computer. After turning on the power of your handheld computer, it will start with the operating system (OS) such as Windows XP.

Boot up

When turning on the power, your handheld computer will start loading the OS into the system memory. This start-up procedure is called “boot up”.

Power on Self Test (POST)

Each time when your handheld computer is turned on, BIOS will automatically perform a self-test of CPU, memory, hardware devices, and so on.

Stop Using Your Handheld Computer

Each time when you finish working with your handheld computer, there are several ways to stop your handheld computer from operating.

Shut down

Directly click “Shut down” from your OS such as Windows XP to turn OFF the power of your handheld computer.

Before shutting down, please always remember to save the unfinished works and close the application for preventing from any possible data loss or HDD damage.

“Shut down” will totally turn OFF the power of your handheld computer. If you want to start your handheld computer again, you need to press the power button.

Standby

Under “Standby” mode, the system will temporarily save your work into RAM. If you want to start your handheld computer again, all you need to press any key.

You are able to do enter “Sleep” mode by directly clicking “Start” => “Shut down” => “Standby” from your OS such as Windows XP. Or, you can do the “Sleep” Mode settings in your OS.

Hibernate

Under “Hibernate” mode, the system will save your work into HDD. If you want to start your handheld computer again, you need to press the power button.

You are able to do enter “Hibernate” mode by setting from your OS such as Windows XP.

Using Indicators and Keypad

Your handheld computer is designed with a keypad for easy and quick operation. Also, each LED indicator shows different meanings.

Here are the descriptions for each button and LED indicator to help you use well with your handheld computer.

Indicators



Power Indicator: Green (Power); Flashing Red (S3: Standby); Consistent Green + Flashing Red (Battery power is lower than 15% under S3 mode)



Charger Indicator: Orange



SSD Indicator: Green (SSD); Red (Input Lock)



Wireless Devices Indicator: Blue

Keypad Hotkey

Before using the keypad functions, please install the Device Power Manager application to activate the hotkeys.

1st Layer:

1. Text Input
2. Application Menu
3. Power On/Off
4. Volume Up
5. Volume Down
6. Mouse's Left Button
7. Invisible Mode On/Off
8. Camera
9. Mouse's Right Button
10. Screen Rotation
11. Login
12. Function Key



2nd Layer:

- a. Fn + Invisible Mode On/Off = Keypad Backlight On/Off
- b. Fn + Volume Up/ Down = LCD Brightness Up/ Down
- c. Fn + Application Menu = Input Lock

Using Application Menu

Application Menu is a hotkey to help you directly access to the functions you often use. Device Power Manger includes the driver of the keypad hotkeys. Do remember to install this application before activating the keypad hotkeys.


Please see the followings for the illustrations:




Using Touch Screen

Your handheld computer is equipped with a high sensitive touch panel allowing you to navigate on the touch screen easily without using any other devices such as external keyboard or mouse. Before using touch screen, please follow the illustrations as below to make your stylus pen for a more precise positioning:

1. Click “Configure” to start.



2. Use “Standard Calibration” and follow the instructions.



A stylus pen is provided for you to use well with the touch screen. Here are some operating tips to help you use the touch screen well with a stylus pen.

- Single Click: Tapping the touch screen with a stylus pen gently
- Double Click: Tapping the touch screen quickly twice with a stylus pen
- Drag and Drop: Clicking and holding the object with a stylus pen slightly and moving to the destination you want (Drag). Leave the stylus pen from the touch screen once you finish dragging (Drop).
- Right Click: Pressing harder on one point of the touch screen and holding for 2~3 seconds. This is the same as using the right click of a mouse.

Note:

- Touch harder with your stylus pen on the icons around the edges.
- Under the direct sunlight for a longer time, the touch screen could heat up over 70°C of a specified maximum temperature.

Using Microphone

It is able for you to record sounds and voices through your handheld computer. Please follow the instruction listed as below to start.

1. Before recording, be sure to enter into Realtek HD Audio Manager, and do the same setting as the picture.

Set the microphone as your recording tool and then click OK to confirm.



2. Please make the sound sources close to the microphone for having better quality.



Note:


- The microphone is located in the middle.

3. Start recording with your recorder such as Sound Recorder in Windows XP.
(Start => Programs => Accessories => Entertainment => Sound Recorder)

Using Fingerprint Sensor (Optional)


Your handheld computer provides a fingerprint sensor for user to strengthen the authentication and security. The followings are steps to set your fingerprint through it.

1. Read from the utility DVD to install “DigitalPersona” and the driver.
2. Open “DigitalPersona”
3. Click “Next” to start the setting.




After Opening “DigitalPersona Personal”, please click “Next” to start the settings.

3. You are able to Practice first.



4. Or, directly set up.



Operating Wireless Devices

For a new designed handheld computer with strong communication features, you are able to turn ON/OFF your Wireless Devices through the proprietary application - "Device Power Manager".

Bluetooth

Bluetooth is a standard wireless device along with your handheld computer. A Class 2, Bluetooth® v2.1 + EDR system is backward compatible with v1.1/1.2/2.0 devices. It will support your handheld computer a short-range wireless communication to connect with other devices.

To activate your Bluetooth function, please follow the illustrations as below.

1. Driver & Application Installation

a. Install the Bluetooth driver first

Read from the Utility DVD and find the directory in readme to finish installation.

b. Then, install the Device Power Manager application
Read from the Utility DVD and find the directory in readme to finish
installation.

2. Launch the Device Power Manager
After launching the utility, please click “Bluetooth”
for enabling the Bluetooth function (click again for
disabling the Bluetooth function).

Once the Bluetooth function starts up, the Wireless
LED indicator will turn on in blue and the Bluetooth
icon will show up in the OS accordingly.

Click “Bluetooth” for enabling the Bluetooth
function (click again for disabling the Bluetooth
function).



Wireless LAN (Optional)

Wireless LAN card is an optional device for your handheld computer. For supporting IEEE 802.11 a/b/g/n, wireless LAN card and embedded antenna will be pre-installed in your handheld computer to access the internet wirelessly.

To activate your Wireless LAN function, please follow the illustrations as below.

1. Driver & Application Installation

a. Install the Chipset Driver first:

Read from the Utility DVD and find the directory in readme to finish installation.

b. Then, install the Device Power Manager application:

Read from the Utility DVD and find the directory in readme to finish installation.

2. Launch the Device Power Manager

After launching the utility, please click “Wireless LAN” for enabling the Wireless LAN function (click again for disabling the Wireless LAN function).

Once the Wireless LAN function starts up, the Wireless Device LED indicator will turn on in blue and the Wireless LAN icon will show “connected” in the OS accordingly.

Click “Wireless LAN” for enabling the Wireless LAN function (click again for disabling the Wireless LAN function).



Note:

- Since this handheld computer does not support cell phone function, but users are able to make phone calls through VOIP when equipped with Wireless LAN function.

WWAN (Optional)

WWAN is an optional module for your handheld computer. With pre-installed embedded antenna and the optional 3.5G WWAN module, your handheld computer will be able to do the telecommunication after installing with a 3.5G SIM card.

1. Insert the SIM card
 - a. Turn OFF your handheld computer.
 - b. Open the lock cover.



- c. Pull up the lock cover.



- d. Put the SIM card into the SIM card slot.
 - e. Lock the cover.

2. Driver & Application Installation

a. Install the WWAN driver first:

Read from the Utility DVD and find the directory in readme to finish installation.

b. Install the Device Power Manager application:

Read from the Utility DVD and find the directory in readme to finish installation.

3. Launch the Device Power Manager

After launching the application, please click “WWAN” for enabling the WWAN function (click again for disabling the WWAN function).

Once the WWAN function starts up, the Wireless Device LED indicator will turn on in blue.

Click “WWAN” for enabling the WWAN function (click again for disabling the WWAN function).



GPS (Optional)

GPS is an optional module for your handheld computer. This GPS module supports GPS and Galileo systems

1. Driver & Application Installation:

a. Install the Device Power Manager application:

Read from the Utility DVD and find the directory in readme to finish installation.

b. Install the GPS driver:

First, please enter into Device Power Manager to turn GPS ON. The screen will display "Found New Hardware Wizard". Then select "No, not this time" => "Install from a list.... (Advanced)" => "Include this location in the search: DB6\Drivers\XP\GPS LEA-5H\Windows WinXP\Driver", then follow the prompt to complete installation.

GPS (Driver): Read from the Utility DVD and find the directory in readme to finish installation.

GPS (Application): Read from the Utility DVD and find the directory in readme to finish installation.

b. Install the Device Power Manager Application:
Read from the Utility DVD and find the directory in readme to finish installation.

Click "GPS" for enabling the GPS function
(click again for disabling the GPS function).



Using Camera (Optional)

Your handheld computer provides an optional 2 million-pixel CMOS camera for you to capture images at any time. Also, it supports video recording function for more application. You are able to press the camera button or application menu button to enter into the camera window as below.



Taking Pictures

Click  in the camera window to take pictures. Or, you can press the camera button again to capture the images.

After taking pictures, your pictures will automatically be saved in C:\Documents and Settings\Administrator\My Document\My Pictures.

Recording Video

Click  in the camera window to recording video. To stop recording, please click . While recording, you can also adjust the volume.

After recording video, your video files will automatically be saved in C:\Documents and Settings\Administrator\My Document\My Video.

Other Functions



Video Format Properties: Advanced video format adjusting



Image Properties: Advanced image settings and camera control



Volume Level: Adjust video recording volume



Flash LED Settings: Advanced flash LED settings



Exit: Exit the camera window/ function

Note:

- For the designed consideration, we suggest you rotate your screen vertically while using the camera.

Chapter Three- Managing Power

Charging Battery

An AC adapter, an AC power cord and a battery are required during battery charging. These are standard accessories for your handheld computer. Do always use the AC adapter, the AC power cord and the battery designed for your handheld computer.

After unpacking your handheld computer, the first thing you need to do is starting charging battery for the further use. Please connect your AC power cord and AC adapter well with the plug and mount your battery well before starting charging. We suggest you to charge the battery for about 8 hours at the very beginning to give a full charge for your battery.

When the battery is nearly exhausted, please save and close the files you are currently working on, and plug in the AC adapter to recharge the battery or swap with a charged battery.

Checking the Battery Level

After a full charge of your battery, you are now able to check your battery level by using the battery meter function of your OS. The battery icons which show the conditions of the battery or where the power source comes from may be different depending on the OS you install.

When the battery is nearly exhausted, the OS will show a warning icon. Also, the Power Indicator LED will flash green when the battery level is under 15%.

Power Conservation

This computer consumes much less power than conventional computers. However, power consumption may be reduced by configuring the Power Management Setup properly.

It is recommended the power saving functions to be enabled even when not running on battery power. Power Management will not degrade performance while saving power.

Replacing Battery

When the battery is nearly exhausted, there are two ways to keep your handheld computer working. Connect the AC adapter and the power cord designed for this handheld computer to start charging is one method; directly replace a charged battery designed for this handheld computer may be the other one.

Note:

- Always remember to turn OFF the power before replacing the battery.
- You can change the battery in 30 seconds under standby mode; otherwise, it may cause the data loss or malfunction of your handheld computer.

Power Saving Tips

- Turn OFF the LCD backlight when not using the handheld computer.
- Lower the intensity of the LCD backlight.
- Use well with Shut down, Standby and Hibernation.
- Use well with the power management settings in your OS.

Supporting ACPI

Your handheld computer supports ACPI (Advanced Configuration and Power Interface) for power management. With ACPI and an ACPI-compliant operating system such as Windows, the feature will allow you to reduce the power consumption for energy saving. By supporting ACPI, the AC adapter LED and the Power indicator LED will show in different ways. The followings are the detailed description.

Standby:

Power LED indicator is ON; Other LED indicators are OFF

Under Hibernation:

All LED indicators are OFF

Shutdown:

All LED indicators are OFF

AC Adapter and AC Power Cord Safety

There are specific power requirements for your handheld computer:

- Only use an approved AC adapter designed for this computer.
- LED?
- There is a 3-prong grounded plug of the AC adapter. The third prong is an important for safety. Do not neglect the importance for it. If you are not able to access a compatible outlet, installing one by a qualified electrician is necessary.
- When unplugging the AC power cord, please be sure to disconnect it from the plug head but from its wire.
- Make sure the socket and any other extension cord you use can support the total current load of all the connected devices.
- Before cleaning the computer, make sure it is disconnected from any external power supplies.

Battery Precautions

- Only use the batteries designed for this computer. The wrong battery may cause explosion, leakage or damage to the computer.
- Do not remove the battery from the computer while it is powered on.
- Do not continuously use a battery that has been dropped, or that appears damaged (e.g. bent or twisted) in any way. Even if the computer is able to continuously work with a damaged battery, the circuit damage may occur and possibly cause fire.
- Always use the charger designed for this handheld computer to recharge the battery. Incorrect recharging may make the battery explode.
- Do not try to repair a battery by yourself. Refer to any battery repair or replacement, please contact with to your service representative.
- Please dispose of a damaged battery promptly and carefully. Explosion or leakage may occur, if the battery is exposed to fire, improperly handled or discarded.

 ***Warning***

Before any upgrade procedures, make sure the power is turned off, and all the cables are disconnected (including telephone lines). Also, it is advisable to remove your battery in prevent from turning the computer on accidentally.

 ***Battery Disposal & Caution***

The product that you have purchased contains a rechargeable battery. The battery is recyclable. At the end of its service life, under various state and local laws, it may be illegal to dispose of this battery into the municipal waste stream. Check with your local solid waste officials for details in your area for recycling options or proper disposal. Danger of explosion may possibly occur, if the battery is incorrectly replaced. Replace only with the same or the equivalent battery recommended by the manufacturer. Discard the used battery according to the manufacturer's instructions.

Chapter Four- BIOS Setup

Before you entering into the BIOS menu, please connect a USB keyboard with your handheld computer.

After the USB keyboard is connected, turn the power of your handheld computer ON and press “Del” on the USB keyboard to directly entering into the BIOS Menu.


Main Menu

In Main Menu, you are able to see the System Overview and the operating instructions.

BIOS SETUP UTILITY				
Main	Advanced	Boot	Security	Exit
System Overview		Use [Enter], [TAB] or [SHIFT-TAB] to select a field.		
AMIBIOS		Use [+] or [-] to configure system Time.		
Version	: 08.00.15			
Build Date	: 03/01/10			
ID	: 1AAAAA000			
Processor				
Intel (R) Atom (TM) CPU Z530 @ 1.60GHz				
Speed	: 1600MHz			
Count	: 1			
System Memory		← Select Screen		
Size	: 2043MB	↑↓ Select Item		
System Time [16:15:25]		-/+ Change Values		
System Date [Thu 05/20/2010]		Tab Select Field		
CMC Lo-Module: OD2.026x, Hi-Module:OD2.018x		F1 General Help		
		F10 Save and Exit		
		Esc Exit		

Advanced Menu

In Advanced Menu, you are able to do the advanced settings.



The screenshot shows the BIOS Setup Utility interface. At the top, a blue header bar contains the text "BIOS SETUP UTILITY". Below this, a navigation bar with a blue background and white text lists the menu options: "Main", "Advanced" (which is highlighted with a white background), "Boot", "Security", and "Exit". The main content area has a grey background and is titled "Advanced Settings". A warning message reads: "Warning: Setting wrong values in below sections may cause system to malfunction." Below the warning, a section titled "► DEVICES Control" lists three settings: "Thermal cooling trip point" with a value of "[79C]", "Critical trip point" with a value of "[103C]", and "Installed O/S" with a value of "[Win/ XP DOS]". On the right side of the screen, a legend lists navigation controls: a left arrow for "Select Screen", up and down arrows for "Select Item", "Enter" for "Go to Sub Screen", "F1" for "General Help", "F10" for "Save and Exit", and "Esc" for "Exit".

BIOS SETUP UTILITY				
Main	Advanced	Boot	Security	Exit
Advanced Settings				
Warning: Setting wrong values in below sections may cause system to malfunction.				
► DEVICES Control				
Thermal cooling trip point	[79C]			
Critical trip point	[103C]			
Installed O/S	[Win/ XP DOS]			
←	Select Screen			
↑↓	Select Item			
Enter	Go to Sub Screen			
F1	General Help			
F10	Save and Exit			
Esc	Exit			

Boot Menu

In Boot Menu, you are able to do the boot settings.

BIOS SETUP UTILITY				
Main	Advanced	Boot	Security	Exit
Boot Settings				Specifies the boot sequence from the available devices.
1st Boot Device		[USB]		A device enclosed in parenthesis has been disabled in the corresponding type menu.
2nd Boot Device		[SATA: PM- PATA SSD]		
3rd Boot Device		[CD/DVD]		
4th Boot Device		[Removable Dev.]		
				← Select Screen
				↑↓ Select Item
				Enter Go to Sub Screen
				Tab Select Field
				F1 General Help
				F10 Save and Exit
				Esc Exit


Security Menu

In Security Menu, you are able to do the security settings.

BIOS SETUP UTILITY				
Main	Advanced	Boot	Security	Exit
Security Settings		Install or Change the password.		
Supervisor Password	:Not Installed			
User Password	:Not Installed			
Change Supervisor Password				
Change User Password				
		← Select Screen		
		↑↓ Select Item		
		Enter Change		
		F1 General Help		
		F10 Save and Exit		
		Esc Exit		

Exit Menu

In Exit Menu, you are able to do the exit option settings.



BIOS Setting for Windows 7 Installation

BIOS SETUP UTILITY				
Main	Advanced	Boot	Security	Exit
Exit Options		Load Optimal Default values for all the setup questions.		
Save Changes and Exit		F9 key can be used for this operation.		
Discard Changes and Exit				
Discard Changes				
Load Optimal Defaults				
Load Failsafe Defaults				
		← Select Screen		
		↑↓ Select Item		
		Enter Go to Sub Screen		
		F1 General Help		
		F10 Save and Exit		
		Esc Exit		

BIOS SETUP UTILITY	
Main	Advanced
<p>Advanced Settings</p> <p>Warning: Setting wrong values in below sections may cause system to malfunction.</p> <p>► DEVICES Control</p> <p>Thermal cooling trip point [79C] Critical trip point [103C] Installed O/S [Windows 7]</p>	
<p>Options</p> <p>Win XP/ DOS Windows 7 Linux</p> <p>← Select Screen ↑↓ Select Item Enter Go to Sub Screen F1 General Help F10 Save and Exit Esc Exit</p>	

BIOS SETUP UTILITY			
Main	Advanced	Boot	Exit
Exit Options		Exit system setup after saving the changes.	
Save Changes and Exit Discard Changes and Exit Discard Changes Load Optimal Defaults Load Failsafe Defaults		F10 key can be used for this operation.	
		← Select Screen ↑↓ Select Item Enter Go to Sub Screen F1 General Help F10 Save and Exit Esc Exit	

Chapter Five- Drivers and Applications

The Utility DVD includes all the drivers for the installed devices in your handheld computer. Please consult the dealer if there is any driver missing.

Also, through Device Manager in Windows, you are able to perform “Driver Update” or check if there are still drivers for the devices needed to be installed.

Check readme.txt file on Utility DVD to get the newest information before starting to install drivers.

Note:

- Please install the chipset driver first.
- If there is any “reboot” showed while installing. Please follow the instructions to reboot first and then install next driver.

Chipset

Read from the Utility DVD and find the directory in readme to finish installation.

Graphic Controller

Your handheld computer supports Intel® GMA500 giving you a flexible, programmable architecture that supports high-definition video decode and image processing. Please follow the installation as below to use well with Intel® GMA500.

Read from the Utility DVD and find the directory in readme to finish installation.

Touch Screen

Your handheld computer is equipped with a high sensitive touch panel. Please follow the installation as below to start using your touch screen.

Read from the Utility DVD and find the directory in readme to finish installation.

Stickpointer

Stickpointer helps you to navigate your cursor on the screen. Please follow the installation as below to start using your stickpointer.

Read from the Utility DVD and find the directory in readme to finish installation.

Audio

Your handheld computer provides a high-quality audio sound effect for user to enjoy better sound quality. To activate this function, please follow the installation as below.

Read from the Utility DVD and find the directory in readme to finish installation.

Fingerprint Sensor (Optional)

Your handheld computer provides a fingerprint sensor for user to strengthen the authentication and security. To activate this function, please follow the installation as below.

Read from the Utility DVD and find the directory in readme to finish installation.

Wireless Devices

Your handheld computer supports wireless communication. Bluetooth is a standard equipped wireless device. If your model supports optional wireless connection, please see the followings to install the drivers and applications.

Bluetooth

Read from the Utility DVD and find the directory in readme to finish installation.

WLAN (Optional)

Depending on the model you choose; if your handheld computer is equipped with a WLAN model, please follow the installation as below to connect your handheld compute with the internet wirelessly.

Read from the Utility DVD and find the directory in readme to finish installation.

WWAN (Optional)

Depending on the model you choose; with pre-installed embedded antenna and the optional 3.5G WWAN module, DB6 will be able to do the telecommunication after installing with a 3.5G SIM card. Please follow the installation as below.

Read from the Utility DVD and find the directory in readme to finish installation.

Note:

- Please see DB6 Technical Reference for more WWAN installation information.

GPS (Optional)

Depending on the model you choose; being able to activate the function, please follow the installation as below.

First, please enter into Wireless Device Power Manager to turn GPS ON. The screen will display "Found New Hardware Wizard". Then select "No, not this time" => "Install from a list.... (Advanced)" => "Include this location in the search: DB6\Drivers\XP\GPS LEA-5H\Windows WinXP\Driver", then follow the prompt to complete installation.

GPS (Driver): Read from the Utility DVD and find the directory in readme to finish installation.

GPS (Application): Read from the Utility DVD and find the directory in readme to finish installation.

.

Device Power Manager

Device Power Manager is an exclusive application designed and developed for the Wireless Devices of your handheld computer. Through Device Power Manager, turning the power ON or OFF become more convenient for being one of the power-saving tips.

Read from the Utility DVD and find the directory in readme to finish installation.

Note:

- The driver of AutoHotkey has been packed in Device Power Manager. To activate the keypad hotkeys, please do remember to install this application.

Gigabit LAN (Optional)

Gigabit LAN function is also supported in your handheld computer. Users are able to surf the internet with the optional Gigabit LAN kit.

Read from the Utility DVD and find the directory in readme to finish installation.

Chapter Six- Specification

Standard System Unit

CPU

- Intel® Atom™ Processor Z530 1.6GHz
- 512 KB L2 Cache
- 533 MHz FSB

Memory

- DDR2 2GB at 533 MHz

Graphic Controller

- Intel® GMA (Graphics Media Accelerator) 500
- Supporting Microsoft® DirectX 9 and Open GL 1.1
- Sharing Max. 509MB System Memory

HDD

- 1.8 PATA SSD (Solid State Disk)
- IDE Interface

Audio

- HD Audio Codec and Amplifier
- Mono Speaker

Display

- 5" WVGA TFT LCD
- 800 x 480 Resolution
- Sunlight-readable with Rugged Touch Screen
- Anti-glare, Anti-reflective Screen Treatments
- 300-nits Brightness with LED Backlight

Communication

- Bluetooth® V2.1 + EDR (Class 2)

I/O Ports

- USB 2.0 x 1
- SD Card Slot x 1
- SIM Card Slot x 1

Battery

- 7.4V, 3900mAh Lithium-ion Battery
- 4-hour Operating Time

AC Adapter

- 36W AC 100V-240V 50/60Hz
- Auto Sensing/ Switching Worldwide Power Supply

Dimensions & Weight

- 200mm (L) x 94mm (W) x 36 mm (H)
- 690g (With all wireless devices and battery)

Case Material & Colors

- Magnesium Alloy
- Black and NATO Green

Certification

- CE
- FCC
- WEEE
- REACH
- MIL-STD-810G
- IP55 (DB6-I)/ IP65 (DB6-M)
- MIL-STD 461F (DB6-M: Standard/ DB6-I: Optional)

Optional Devices and Accessories

Camera

- 2 Million-pixel CMOS Camera with Flashlight
- Supporting Video Recording

Communication

- Wireless LAN Card: Supporting IEEE 802.11 a/b/g/n
- WWAN: HSDPA/UMTS 3.5G
- GPS: Ublox LEA-5H
- Sealed Gigabit LAN (Trade-off with WLAN/ Location 1 or 2)

I/O Ports

- Sealed USB (Location 1 or 2)
- Sealed Audio (Location 1 or 2)
- Expansion Connector (Location 5)

Security

- Fingerprint Reader

Carry Bag

Vehicle Power Cord

Chapter Seven- Maintenance and Service

Cleaning

ALWAYS turn OFF the power, unplug the power cord and remove the battery before cleaning.

The exterior of the system and display may be wiped with a clean, soft, and lint-free cloth. If there is difficulty removing dirt, apply non-ammonia, non-alcohol based glass cleaner to the cloth and wipe.

An air gun is recommended for cleaning water and dust. For salty water please clean with fresh water then blow-dry with an air gun. Be sure not to turn the computer up side down while there is water being applied.

Troubleshooting

Should the computer fail to function properly, the troubleshooting steps below may be followed.

- Check AC/vehicle adapter, battery, and the power source.
- Minimize the configuration, i.e. remove extra peripherals and devices.
- Remove the software suspected.
- Set BIOS fail-safe default.
- Re-install operating system and application software.

RMA Service

If troubleshooting steps are unsuccessful, consult your dealer for RMA.

Shipping instructions:

1. Remove any personal data.
2. Use the original shipping container and packing materials, if possible.
3. If the original packing materials are not available, wrap the equipment with soft material (e.g. PU/PE form) then put the wrapped equipment into a hard cardboard shipping box.
4. Include a sheet with the following information: (Note: Please keep a copy of this sheet for your records)
 - Name
 - Address
 - Unit serial number
 - Place and date of purchase or the original invoice number
 - Date of failure
 - A DETAILED Description of the problems you have encountered
 - A list of the hardware/software configuration, if applicable.

5. Clearly mark the outside of the shipping box with the RMA #. If RMA # is not present on the shipping box, receiving will be unable to identify it and it might be returned.
6. Unless prior arrangements have been made, the customer is responsible for all shipping costs. Unauthorized use of the company's shipping accounts is not permitted.